

**P - Type "Quick Lock" Triple Row**

<p><b>Plug Housing</b> (load with Female Contact)</p> <p>Order Code Housing: <b>PCF-3xx-P635/X</b></p>	<p><b>Clutch Housing</b> (load with Male Contact)</p> <p>Order Code Housing: <b>PCC-3xx-P635/X</b></p>
<p><b>Female Contact</b></p> <p>Order Code: <b>PCF-999/xx-P635-99</b>      MOQ: 10K / reel</p>	<p><b>Male Contact</b></p> <p>Order Code: <b>PCM-999/xx-P635-99</b>      MOQ: 10K / reel</p>

**Fully Shrouded Header**

<p><b>-THT- Female</b>      straight (top entry)</p> <p>Order Code: <b>PCS-3xx-PF635-99/X</b></p>	<p><b>-THT- Male</b>      straight (top entry)</p> <p>Order Code: <b>PCS-3xx-PM635-99/X</b></p>
---	---

**Specifications**

Current rating      13 A (5-10 pos. 11 A)	Voltage rating      600 V AC max.	Contact material    Copper Alloy
Insulation resistance    1000 MΩ min.	Withstanding voltage    1000 V AC	Insulator material    PA66    UL 94V-0 & V-2
Contact resistance      20 mΩ max.	Operating temperature    -55°C to +105°C	PCB thickness        1.60mm

**How to order**

**PC X - x xx - X 635 - 99 / X**

<p><b>Type</b></p> <p><b>C</b> = Clutch <b>F</b> = Female <b>M</b> = Male <b>S</b> = Straight</p>	<p><b>Rows</b></p> <p><b>3</b> = triple row</p> <p><i>if Crimp Contact:</i> <b>9</b></p>	<p><b>Nbr of Contacts</b></p> <p>P, PF &amp; PM – Execution: <b>06, 09, 12 &amp; 15</b></p> <p><i>if Crimp Contact:</i> <b>99/10</b> = for AWG 12~14 <b>99/16</b> = for AWG 16~20 <b>99/19</b> = for AWG 18~22</p>	<p><b>Execution</b></p> <p><b>P</b> = P - Type <b>PM</b> = P - Type male <b>PF</b> = P - Type female</p> <p style="text-align: center; font-size: small;">for details see above dwg's</p>	<p><b>Plating</b></p> <p><b>99</b> = Tin <i>(leadfree)</i></p> <p style="text-align: center; font-size: small;">other platings on request</p>	<p><b>Color Option</b></p> <p><b>N</b> = nature (UL 94V-2) <b>W</b> = white (UL 94V-0)</p> <p style="text-align: center; font-size: small;">PF &amp; PM Execution if polarizing is requested:</p> <p><b>NP</b> = nature (UL 94V-2) <b>WP</b> = white (UL 94V-0)</p>
---	--	--	---	---	---